



- Motion Labs 12 channel modular motor control and power distribution system.
- 208 Input (G, X, Y, Z) 3 Phase 4 Wire
- Dual Twist output rated for up to 12 1HP 3 Phase Electric Chain Hoists.
- Phase Reverse option to correct out of phase input.
- Contactor Enable button for local pendant control.
- Handheld Remote utilizes momentary switch for GO function and maintained switch for KILL function.
- KILL function disengages power to the motors.
- Unit built into 17 space 1 lid NEMA 1 Steel Liner.
- Unit is ETL Listed in Canada and the United States and conforms to UL Standards 1640 for Portable Power Distribution and UL 508A for Industrial Controls as well as Canadian CSA Standard C22.2 No. 14
- Qualified Personnel Only

Type 1 Enclosure  
 Indoor Use Only  
 Input Voltage: 208VAC 3PH 60Hz  
 Wiring Config: 12 CH @ 1HP  
 Max Ampacity: 50 Amps  
 Part No.: 1200-12-C-M-0703  
 Serial No.: XXXX

208 VAC  
 3PH 60 Hz  
 10 AMPS MAX.  
 PINDOUT: 0900-01  
 L16-20  
 X = L1  
 Y = L2  
 Z = L3  
 Green = Ground  
 L14-20  
 X = Common  
 Y = Down  
 W = Up  
 G = Not Used



**motionlaboratories**  
 520 Furnace Dock Road Cortlandt Manor, NY 10567  
 800-227-6784

Copyright © 2008, Motion Laboratories, Inc. All Rights Reserved. THIS DOCUMENT IS THE EXCLUSIVE CONFIDENTIAL PROPERTY OF MOTION LABORATORIES, INC. AND IT SHALL NOT BE REPRODUCED, COPIED, OR USED FOR ANY PURPOSE WHATSOEVER, UNLESS, AND STRICTLY TO THE EXTENT, SUCH IS EXPRESSLY AUTHORIZED BY MOTION LABORATORIES, INC. IN WRITING.

<b>TITLE</b>		<b>SCALE</b>		<b>REV</b>
Motor Control, 12 CH, Input 50A 480V 3PH, DT L16-20 Pwr L14-20 Ckt, PO-3A-A10900-01, 6X10A3P, 17-1, w/Handheld		---		-
<b>DRAWN BY</b>	<b>DATE DRAWN</b>	<b>SIZE</b>	<b>DRAWING NUMBER</b>	
-	-	A	1200-12-C-M-0703	
<b>CHECKED BY</b>	<b>DATE CHECKED</b>	<b>MODEL FILENAME &amp; PATH</b>		
-	-	---		
<b>SCALE</b>	<b>SHT</b>	<b>OF</b>		
---	1	1		