



- Motion Labs 12 channel modular motor control and power distribution system.
- 208 input (G, X, Y, Z) 3 Phase 4 Wire
- Ceep 7 output rated for up to 12 1HP 3 Phase Electric Chain Hoists.
- Phase Reverse option to correct out of phase input.
- Contactor Enable button for local pendant control.
- Handheld Remote utilizes momentary switch for GO function and maintained switch for KILL function.
- KILL function disengages power to the motors.
- Unit built into 12 space 1 Ild NEMA 1 Steel Liner.
- Unit is ETL Listed in Canada and the United States and conforms to UL Standards 1640 for Portable Power Distribution and UL 508A for Industrial Controls as well as Canadian CSA Standard C22.2 No. 14
- Qualified Personnel Only

Type 1 Enclosure
Indoor Use Only
 Input Voltage: 208VAC 3PH 60Hz
 Wiring Config: 12 CH @ 1HP
 Max Ampacity: 50 Amps
 Part No.: 1200-12-C-M-1313-03
 Serial No.: XXXX

208VAC
 3PH 60 Hz
 10 AMPS MAX.
 PINOUT: C7-38
 1 = L1
 2 = L2
 3 = L3
 4 = UP
 5 = GROUND
 6 = MTR COMMON
 7 = MTR DOWN



motion laboratories
 520 Furnace Dock Road Cortlandt Manor, NY 10567
 800-227-6784

Copyright © 2016, Motion Laboratories, Inc. All Rights Reserved. THIS DOCUMENT IS THE EXCLUSIVE CONFIDENTIAL PROPERTY OF MOTION LABORATORIES, INC. AND IT SHALL NOT BE REPRODUCED, COPIED, OR USED FOR ANY PURPOSE WHATSOEVER, UNLESS, AND STRICTLY TO THE EXTENT, SUCH IS EXPRESSLY AUTHORIZED BY MOTION LABORATORIES, INC. IN WRITING.

TITLE		Motor Control, 12 CH, Input 208V 3PH 50A 480V FI, C7, C7-38 6X10A3P, 12-1, w/Handheld
DRAWN BY	DATE DRAWN	SIZE
CHECKED BY	DATE CHECKED	A
MODEL FILENAME & PATH		DRAWING NUMBER
		1200-12-C-M-1313-03
SCALE	SHT	REV
----	1	-
	OF	
	1	