



- Motion Labs 12 channel modular motor control and power distribution system.
- 208 Input (G, X, Y, Z) 3 Phase 4 Wire
- P-14 output rated for up to 12 1HP 3 Phase Electric Chain Hoists.
- Phase Reverse option to correct out of phase input.
- Contactor Enable button for local pendant control.
- Handheld Remote utilizes momentary switch for GO function and maintained switch for KILL function.
- KILL function disengages power to the motors.
- Unit built into 12 space 1 lld NEMA 1 Steel Liner.
- Qualified Personnel Only

Type 1 Enclosure
Indoor Use Only
 Input Voltage: 208VAC 3PH 60Hz
 Wiring Config: 12 CH @ 1HP
 Max Ampacity: 50 Amps
 Part No.: 1200-12-C-M-1414
 Serial No.: XXXX

208VAC
 3PH 60 Hz
 10 AMPS MAX.
 PINOUT: P14-01
 A = L1
 B = L2
 C = L3
 D = MTR UP
 E = MTR COMMON
 F = MTR DOWN
 N = GROUND



motion laboratories
 520 Fumace Dock Road Cortlandt Manor, NY 10567
 800-227-6784

Copyright © 2018 Motion Laboratories, Inc. All Rights Reserved. THIS DOCUMENT IS THE EXCLUSIVE PROPERTY OF MOTION LABORATORIES, INC. AND SHALL NOT BE REPRODUCED, COPIED, OR USED FOR ANY PURPOSE WHATSOEVER, UNLESS AND STRICTLY TO THE EXTENT SUCH IS EXPRESSLY AUTHORIZED BY MOTION LABORATORIES, INC. IN WRITING.

TITLE		DRAWN BY		DATE DRAWN		SIZE		DRAWING NUMBER		REV	
Motor Control, 12 CH, Input 208V 3PH 50A 480V FI, P14, 6X10A3P, 12-1, w/Handheld		-		-		A		1200-12-C-M-1414		-	
MODEL FILENAME & PATH		CHECKED BY		DATE CHECKED		SCALE		SHT		OF	
-		-		-		-		1		1	