



- Motion Labs 8 channel modular motor control and power distribution system.
- 208 Input (G, X, Y, Z) 3 Phase 4 Wire
- P-14 output rated for up to 8 1HP 3 Phase Electric Chain Hoists.
- Phase Reverse option to correct out of phase input.
- Contactor Enable button for local pendant control.
- Handheld Remote utilizes momentary switch for GO function and maintained switch for KILL function.
- KILL function disengages power to the motors.
- Unit built into 8 space 1 lid NEMA 1 Steel Liner.
- Qualified Personnel Only

Type 1 Enclosure
Indoor Use Only
 Input Voltage: 208VAC 3PH 60Hz
 Wiring Config: 8 CH @ 1HP
 Max Ampacity: 40 Amps
 Part No.: 1200-8-C-M-1414
 Serial No.: XXXX

208VAC
 3PH 60 Hz
 TO AMPS MAX.
 PINOUT: P14-01
 A = L1
 B = L2
 C = L3
 D = MTR UP
 E = MTR COMMON
 F = MTR DOWN
 N = GROUND



motion laboratories
 520 Furnace Dock Road Cortlandt Manor, NY 10567
 800-227-6784

Copyright © 2016 Motion Laboratories, Inc. All Rights Reserved. THIS DOCUMENT IS THE EXCLUSIVE CONFIDENTIAL PROPERTY OF MOTION LABORATORIES, INC. AND IT SHALL NOT BE REPRODUCED, COPIED, OR USED FOR ANY PURPOSE WHATSOEVER, UNLESS, AND STRICTLY TO THE EXTENT, SUCH IS EXPRESSLY AUTHORIZED BY MOTION LABORATORIES, INC. IN WRITING.

TITLE		DRAWN BY		DATE DRAWN		SIZE		DRAWING NUMBER		REV	
Motor Control, 4 CH, Input 50A 480V 3PH, P14, 4X10A3P, 8-1, w/Handheld		-		-		A		1200-8-C-M-1414		-	
MODEL FILENAME & PATH		CHECKED BY		DATE CHECKED		SCALE		SHT		OF	
-		-		-		-		1		1	